SMART Pulser mini

Quick Start Guide

First use in 4 steps

1 Power supply

- The SmartPulser mini system can be powered by:
- the supplied USB-C power adapter
- any other suitable USB-C power adapter
- a power bank
- a suitable USB charging socket in a vehicle (car)

Only use power sources that meet the technical requirements (DC 5.0 V, at least 3.0 A, 15 Watt).

2 Connect the applicator

- Plug the applicator connector into the matching socket on the control unit. The logo on the connector must face up.
- Connect only one applicator at a time.
- The applicator is detected automatically. The indicator LEDs show: green = detected, red = not detected or not connected correctly.

3 Switching on and off

- Switch on: press and hold the ON/OFF button for several seconds until the display turns on!.
- Switch off: press and hold the ON/OFF button for about two seconds until the display turns off.
- After about two minutes of inactivity, the device switches to power-saving mode; pressing any button will reactivate it!

Important notes

- Operating temperature: -10 °C to +40 °C.
- Protect the device from moisture; do not operate it in damp rooms.

4 Setting up and starting

- Select the intensity (Intensity +/– buttons) and the session duration (Time +/– buttons).
- Start with the START/STOP button. Animated white indicator LEDs show that the session is running, and the remaining time counts down on the display.
- The session ends automatically; press START/STOP to end it early at any time. Afterwards, the OPTION button restores the most recently used settings.

Applicator	Intensity	Duration
Local applicator	10 / 25 / 50 / 100 / 200 / 400	8 / 16 / 24 min
Pet applicator (S.Pet)	SENS / LOW / MED / HIGH	12 / 24 / 36 / 48 / 60 min
Beauty mask (S.Face)	OFF / 10 / 25 / 50 / 100	8 / 16 / 24 min

- S.Pet – Auto Timer: Press the “Option” button (indicator LEDs light up blue), then use ‘Option’ +/– to set up to four automatic applications per day (the number of lit LEDs indicates the number of applications per day). To deactivate, press the “Option” button again (indicator LEDs flash purple).
- S.Face – Mask: Use the Option key to select the LED color; use Option +/– to adjust the LED brightness. To use the device without PEMF, set the intensity to “OFF.”

Complete user manual

You will find all details, error messages, cleaning, technical data and safety information in the complete user manual. Scan the QR code or visit:

https://smartpulser.com/manuals/

Before first use, please read the complete user manual, especially chapter 13 “Safety instructions”.

Super Captain Co. Ltd. · Version 2026/11